# ZEAL Optics

Update MOD Live Firmware

Whenever firmware updates are released for MOD Live, you will be automatically notified when you connect MOD Live to Recon HQ software on your computer.

Written By: Carl Walker

Step 1 — Update MOD Live Firmware

- First, upgrade MOD Live using the Recon HQ software:
  - Plug MOD Live into your computer.
  - Power on your device.
  - Start Recon HQ software - a prompt will appear notifying you of new firmware and asking if you want to Update Now.
  - Click Yes to initiate the upgrade process - a status bar will display the progress.
  - When the Transfer Complete popup appears, click OK.

Step 2

- Then, follow these steps on your MOD Live:

    - Navigate to the Preferences menu under Settings and select Firmware Upgrade.

    - On the Firmware Upgrade submenu, navigate to and select the option Upgrade Firmware.

    - The next screen provides you with the choice of upgrading or restoring to the factory default.

    - Navigate to and select Upgrade.

    - Select Yes at the confirmation prompt - the firmware upgrade process will begin and a status bar will display the progress.

- Once the firmware update completes, MOD Live will automatically reboot - the display will turn black. When MOD Live restarts, an Android icon appears to let you know that MOD Live storage capacity is changing. MOD Live will reboot again, and the display will turn black.

- Wait about ten seconds and press the MOD Live power button. When MOD Live restarts, the Recon Instruments splash screen appears for a few seconds. Next, an upgrade screen appears with a message saying Updating Apps. After the Update screen disappears, MOD Live is ready to use.

Step 3

- Operational notes:
  - Features and functionality of Recon HQ software are supported by an internet connection as well as Adobe Air version 2.1 or later.
  - Make sure MOD Live is fully charged before performing a firmware update. If your battery is not sufficiently charged and MOD Live loses power during the upgrade, your device can be permanently damaged.
  - To verify you upgraded successfully your device, navigate to Version Number under System Status in the Settings menu.

This document was last generated on 2015-05-05 08:03:27 AM.